

CCTV Microphone



Model: MIC207



Features:

- * This Sound Monitor for CCTV Security System.
- * Shell separation design, easy to ceiling installation.
- * Adopt high-sensitivity omnidirectional capacitive microphone, omnidirectional sound pickup, clear and natural.
- * Support automatic gain control(AGC) adjustment, automatically suppress high-intensity sounds, eliminate sound differences between near and far, makes playback sound clearer and louder.
- * Support anti-reverberation function, sound is real and clear without reverberation in indoor and empty hall scenes.
- * Support multi-level volume adjustment function, the volume can be adjusted by physical knob and external device software two ways.
- * Support centralized power supply, camera power supply, DC power supply, no special power supply required.
- * Power reverse polarity protection, on-site installation and wiring without worries.

Specifications:

- * Operating voltage: DC9V~18V (recommend to use 12V)
- * Audio monitoring range: 5~100 square meter
- * Audio transmission distance: 3000m
- * Frequency range: 20Hz~20KHz
- * Sensitivity: -32dB
- * Directional property: Omnidirectional
- * Output impedance: 600 ohm non-equilibrium
- * Out signal amplitude: 2.5Vpp/-25dB
- * Microphone: Electret condenser microphone
- * Signal processing: automatic Level Control, automatic gain control
- * Protective circuit: Power supply polarity reverse connect protection
- * Driving ability: Built-in preamplifier circuit, which can directly drive headphones
- * Connection way: 3 leading wires(red power lead is positive wire,white audio lead is positive, black is public wire)
- * Color: Green
- * Housing material: Plastic

Packaging:

1 x CCTV Microphone, 1 x Using Manual, 1 x Box

Product information is subject to change without prior notice.